DEFINE

ELECTRICAL ABBREVIATIONS

CT	DENOTES COUNTER-TOP-HEIGHT MOUNTED. CONTRACTOR TO VERIFY COUNTER TOP HEIGHT AND HEIGHT OF BACK SPLASH.
E	DENOTES EMERGENCY DEVICE
G	DENOTES GROUND FAULT INTERRUPTER PROTECTED
WP	DENOTES WEATHERPROOF
AFF	DENOTES ABOVE FINISHED FLOOR
C	DENOTES CONDUIT
A	DENOTES AMP
EWC	ELECTRICAL WATER COOLER
W	WALL MOUNTED-48" ABOVE FINISHED FLOOR OR AS NOTED
CB	CODE BLUE
IG	DENOTES ISOLATED GROUND
FDS	FUSED DISCONNECT SWITCH
BOF	BOTTOM OF FIXTURE
MRR	MANUFACTURER'S RECOMMENDED RATING
WR	WEATHER RESISTANT
VOJ	VERIFY ON JOB
VR	VANDAL RESISTANT
SPD	SURGE PROTECTION DEVICE - REFER TO SPECIFICATIONS.

ELECTRICAL LINE TYPE LEGEND

SCREENED LINES/SYMBOLS INDICATE EXISTING DEVICES TO REMAIN.

DASHED LINES/SYMBOLS INDICATE EXISTING DEVICES TO BE REMOVED OR RELOCATED.

BOLD LINES/SYMBOLS INDICATE NEW OR RELOCATED DEVICES.

SOLID-FILL LIGHTS INDICATE EMERGENCY FIXTURES. CIRCUIT BATTERY PACK AHEAD OF SWITCH.

ELECTRICAL GENERAL DEMOLITION NOTES

1. THE CONTRACTOR IS ALLOWED TO RE-USE EXISTING DEVICES, DISCONNECTS, & PANELS IF THE EQUIPMENT IS IN GOOD WORKING CONDITION. THE CONTRACTOR SHALL CLEAN & REPAIR THE EXISTING DEVICES AS NEEDED IF THE CONTRACTOR CHOOSES TO RE-USE.
2. REMOVE EXISTING LIGHT FIXTURES, DISCONNECTS, OUTLETS, BOXES, WIRING, CONDUIT, ETC. AND OFFER TO OWNER. IF OWNER REFUSES, ELECTRICAL CONTRACTOR SHALL REMOVE FROM SITE AND PROPERLY AND LEGALLY DISPOSE.
3. REMOVE EXISTING DEVICES FROM WALLS BEING DEMOLISHED. IF THEY OCCUR IN THE MIDDLE OF A CIRCUIT, MAKE THE REMAINDER OF THE CIRCUIT CONTINUOUS.
4. MAINTAIN ALL REMAINING EXISTING CIRCUITS WHERE INTERRUPTED BY DEMOLITION WORK. PROVIDE WIRING AND CONDUIT TO RESTORE CONTINUOUS CIRCUIT INTEGRITY.
5. PROTECT EXISTING ELECTRICAL EQUIPMENT AND INSTALLATIONS INDICATED TO REMAIN. IF DAMAGED OR DISTURBED IN THE COURSE OF THE WORK, REMOVE DAMAGED PORTIONS AND INSTALL NEW PRODUCTS OF EQUAL CAPACITY, QUALITY, AND FUNCTIONALITY.
6. CONTACT LOUISIANA ONE CALL FOR IDENTIFICATION OF ALL UNDERGROUND UTILITIES PRIOR TO REMOVAL.
7. EXISTING ROUTING OF CIRCUITS/FEEDERS ARE INDICATED ON DRAWINGS FOR REFERENCE ONLY. CONTRACTOR IS RESPONSIBLE FOR VERIFYING EXACT LOCATIONS OF FEEDERS/CIRCUITS PRIOR TO ANY EXCAVATION. CONTRACTOR SHALL BARE ALL COST OF RESTORING EXISTING ELECTRICAL FUNCTIONALITY SHOULD ANY EXISTING UNDERGROUND ELECTRICAL UTILITIES BE DAMAGED DURING THE COURSE OF CONSTRUCTION.

DESIGN

ELECTRICAL LEGEND

SYMBOL	LIGHTING DESCRIPTION
	LIGHTING FIXTURE-REFER TO LIGHTING FIXTURE SCHEDULE
	LIGHTING FIXTURE-REFER TO LIGHTING FIXTURE SCHEDULE
	LIGHTING FIXTURE-REFER TO LIGHTING FIXTURE SCHEDULE
	LIGHTING FIXTURE-REFER TO LIGHTING FIXTURE SCHEDULE
	CEILING MOUNTED EXIT LIGHT - REFER TO LIGHTING FIXTURE SCHEDULE - ARROWS DEFINE DIRECTION
	WALL MOUNTED EXIT LIGHT - COORDINATE FINAL MOUNTING HEIGHT WITH THE ARCHITECT - REFER TO LIGHTING FIXTURE SCHEDULE - ARROWS DEFINE DIRECTION
	EMERGENCY LIGHT (8'-0" A.F.F. OR AS NOTED) - REFER TO LIGHTING FIXTURE SCHEDULE
	CEILING MOUNTED EGRESS LIGHT - REFER TO LIGHTING FIXTURE SCHEDULE
	PHOTOCELL
$	SINGLE POLE TOGGLE SWITCH (48" A.F.F. TO TOP OF DEVICE BOX OR AS NOTED)
$3	THREE-WAY TOGGLE SWITCH (48" A.F.F. TO TOP OF DEVICE BOX OR AS NOTED)
$D	WALL MOUNTED DIMMER SWITCH WITH ON/OFF AND 0-10V OUTPUT DIMMING. DIMMER MUST BE COMPATIBLE WITH BALLAST OR LED. REFER TO SPECIFICATIONS. PROVIDE ALL NECESSARY CONDUCTORS FOR COMPLETE OPERATING SYSTEM. (48" A.F.F. TO TOP OF DEVICE BOX OR AS NOTED)
$M	MOTOR RATED SWITCH - CONTRACTOR TO PROVIDE SWITCH TO DE-ENERGIZE EACH CURRENT CARRYING CONDUCTOR. LOCATE ADJACENT TO EQUIPMENT BEING SERVED IN A READILY ACCESSIBLE LOCATION.
$K	SINGLE POLE KEYED SWITCH (48" A.F.F. TO TOP OF DEVICE BOX OR AS NOTED)
$-	SWITCH (48" A.F.F. TO TOP OF DEVICE BOX OR AS NOTED) COORDINATE TYPE AND INSTALLATION REQUIREMENTS WITH MANUFACTURER. COORDINATE LOCATION WITH OWNER.
$	SINGLE POLE DIGITAL PRESET COUNT DOWN TYPE TIMER SWITCH (48" A.F.F. TO TOP OF DEVICE BOX OR AS NOTED) SENSORSWITCH PTS 60 OR EQUAL
	WALL MOUNTED VACANCY SENSOR (48" A.F.F. TO TOP OF DEVICE BOX OR AS NOTED) - REFER TO SPECIFICATIONS.
LCD	TOUCHSCREEN LIGHTING CONTROL STATION - ACUITY FCS-7TSN OR APPROVED EQUAL.
	CORNER MOUNTED VACANCY SENSOR - MOUNTING HEIGHT TO BE DETERMINED PER MANUFACTURER'S RECCOMENDATIONS FOR OPTIMAL COVERAGE - MYTECH, WATT STOPPER
	POWER DESCRIPTION
	DUPLEX CONVENIENCE OUTLET (18" A.F.F. FOR GENERAL AREAS, 36" A.F.F. FOR GARAGES, HANGARS AND THE LIKE OR AS NOTED)
TV	TELEVISION OUTLET (VERIFY MOUNTING HEIGHT AND LOCATION WITH ARCHITECT)
EWC	ELECTRICAL WATER COOLER; COORDINATE ELECTRICAL DEVICE/OUTLET TYPE AND LOCATION WITH PLUMBING CONTRACTOR (CONCEAL OUTLET/DEVICE BEHIND COOLER) OUTLET TO BE GROUND FAULT INTERRUPTER PROTECTED.
MW	MICROWAVE OUTLET - RECESSED 20 AMP DUPLEX OUTLET. HUBBELL OR EQUAL. VERIFY EXACT MOUNTING LOCATION WITH OWNER/ACHITECT PRIOR TO ROUGH IN.
WH	WATER HEATER; COORDINATE ELECTRICAL OUTLET/DISCONNECT TYPE AND LOCATION WITH PLUMBING CONTRACTOR
SB	SMART BOARD OUTLET - SB DENOTES HEIGHT OF OUTLET PER OWNER
TR	DUPLEX CONVENIENCE OUTLET (18" A.F.F. OR AS NOTED) TR DENOTES TAMPER RESISTANT - HUBBELL: RR205TR, GFTR20 OR EQUAL.
U	COMBINATION RECEPTACLE/OUTLET AND DUAL USB CHARGER - LEVITON T5832 OR EQUAL. (18" A.F.F. OR AS NOTED)
	DOUBLE DUPLEX CONVENIENCE OUTLET (18" A.F.F. OR AS NOTED)
	SPECIAL OUTLET (VERIFY TYPE AND MOUNTING HEIGHT WITH EQUIPMENT MANUFACTURER)
	COUNTER TOP DUPLEX OUTLET (CLEAR BACK SPLASH)
	CEILING MOUNTED OUTLET
	MOTOR STARTER - PROVIDED BY MECHANICAL CONTRACTOR, INSTALLED BY ELECTRICAL CONTRACTOR.
	FLOOR BOX, POWER (COORDINATE FINAL LOCATION WITH OWNER/ARCHITECT PRIOR TO INSTALLATION) MINIMUM 2-3/4" CONDUITS TO ACCESSIBLE CEILING.
XX	FLOOR BOX, COMBINATION POWER/COMMUNICATIONS WITH 1 DUPLEX CONVENIENCE OUTLET. (COORDINATE FINAL LOCATION WITH OWNER/ARCHITECT PRIOR TO INSTALLATION. 2-1" CONDUITS IN SLAB TO 6" ABOVE ACCESSIBLE CEILING - PROVIDE BLANK PLATE OR XX DENOTES CABLE TYPE AND QUANTITY; P=PHONE, D=DATA, C=COAX REFER TO SPECIFICATIONS
J	JUNCTION BOX
EMS	CONTROL POWER FOR ENERGY MANAGEMENT SYSTEM - PROVIDE OUTLET OR JUNCTION BOX AT LOCATION PER EMS CONTRACTOR
HD	HAND DRYER - COORDINATE OUTLET/DEVICE TYPE WITH SUPPLIER. COORDINATE LOCATION WITH THE OWNER/ARCHITECT PRIOR TO ROUGH-IN.
	ELECTRICAL MOTOR (COORDINATE TERMINATION WITH SUPPLIER)
XX/Y ZZ/Y	FUSED DISCONNECT SWITCH - FUSE AT MANUFACTURER RECOMMENDED RATING UNLESS NOTED OTHERWISE. XX DENOTES DISCONNECT SIZE, Y DENOTES PHASE, ZZF ZZ DENOTES FUSE SIZE.
	ELECTRICAL PANEL SURFACE MOUNTED
	ELECTRICAL PANEL FLUSH MOUNTED
	TELEPHONE/POWER POLE: COORDINATE EXACT MOUNTING LOCATION WITH FURNITURE MANUFACTURER. MAKE FINAL CONNECTIONS. REFER TO DETAIL. WIRE MOLD: 30TP-4V
	CONDUIT RUN CONCEALED IN WALL OR ABOVE CEILING
	CONDUIT RUN CONCEALED UNDER FLOOR OR BELOW GRADE
	HOMERUN TO ELECTRIC PANEL BOARD (INDICATED NUMBER OF CIRCUIT BY NUMBER OF ARROWS)
	THREE (3) CONDUCTORS RUN IN CONDUIT. EVERY CIRCUIT TO HAVE A GROUND, SHARED NEUTRAL IS NOT ALLOWED.
	FOUR (4) CONDUCTORS RUN IN CONDUIT. EVERY CIRCUIT TO HAVE A GROUND, SHARED NEUTRAL IS NOT ALLOWED.
	FIVE (5) CONDUCTORS RUN IN CONDUIT. EVERY CIRCUIT TO HAVE A GROUND, SHARED NEUTRAL IS NOT ALLOWED.
	FOUR (4) CONDUCTORS RUN IN CONDUIT, ONE CONDUCTOR DESIGNATED FOR ISOLATED GROUND
M	MOTORIZED DAMPER - PROVIDE BY OTHERS. ELECTRICALLY POWERED BY ELECTRICAL CONTRACTOR WHEN NOTED.
VFD	VARIABLE FREQUENCY DRIVE PROVIDED BY MECHANICAL AND INSTALLED BY ELECTRICAL. MAINTAIN CLEARANCES PER NFPA 70

SYMBOL	SPECIAL SYSTEMS DESCRIPTION
XX	COMMUNICATIONS OUTLET - DEEP 4" SQUARE BOX WITH SINGLE GANG PLASTER RING WITH CABLE/PULLSTRING IN 1" CONDUIT TO ACCESSIBLE CEILING (18" A.F.F OR AS NOTED) - PROVIDE A BLANK PLATE OR XX DENOTES CABLE TYPE AND QUANTITY; P=PHONE_D=DATA, C=COAX REFER TO SPECIFICATIONS.
XX	TELEVISION OUTLET-DEEP 4" SQUARE BOX WITH SINGLE GANG PLASTER RING WITH CABLE/PULLSTRING IN 1" C. TO ACCESSIBLE CEILING (VERIFY MOUNTING HEIGHT AND LOCATION WITH ARCHITECT) - PROVIDE BLANK PLATE OR XX DENOTES CABLE TYPE AND QUANTITY; P=PHONE, D=DATA, C=COAX REFER TO SPECIFICATIONS
XX	DATA JACK ABOVE CEILING W/ 30' OF SLACK (FUTURE WIRELESS ACCESS POINT) XX - DENOTES CABLE QUANTITY
AV	AUDIO & VISUAL - DEEP 4" SQUARE DEEP DOUBLE GANG BOX WITH DOUBLE GANG PLASTER RING (MOUNT 18" A.F.F. V.O.J.) WITH 1 1/4" CONDUIT WITH CABLE/PULLSTRING TO A MINIMUM OF 6" ABOVE CEILING.
OP	OVERHEAD PROJECTOR - DEEP 4" SQUARE BOX INSTALLED ABOVE CEILING ADJACENT TO OVERHEAD PROJECTOR (SEE DETAIL)
AV	AUDIO & VISUAL - RECESSED FLOOR BOX - WIREMOLD RFB9 OR EQUAL (SEE DETAIL)
SB	SMART BOARD J-BOX - 4" SQUARE DEEP BOX WITH SINGLE GANG PLASTER RING WITH CABLE/PULLSTRING IN 3/4" CONDUIT TO ACCESSIBLE CEILING. (SEE DETAIL)
CB	CONTROL STATION - 4" SQUARE DEEP BOX WITH SINGLE GANG PLASTER RING WITH CABLE/PULLSTRING IN 3/4" CONDUIT TO ACCESSIBLE CEILING. (SEE DETAIL)
	FIRE ALARM DESCRIPTION
P	FIRE ALARM PULL STATION - DEEP 4" SQUARE BOX WITH SINGLE GANG PLASTER RING WITH CABLE IN 3/4" CONDUIT TO ACCESSIBLE CEILING (48" A.F.F. TO TOP OF DEVICE BOX OR AS NOTED)
VS	FIRE ALARM VALVE SUPERVISORY SWITCH- PROVIDE MONITORING MODULE FOR ALL VALVE SUPERVISORY SWITCHES, COORDINATE REQUIREMENTS, QUANTITIES, AND LOCATIONS WITH THE SPRINKLER CONTRACTOR
WF	FIRE ALARM FLOW DETECTOR/SWITCH - PROVIDE MONITORING MODULE FOR ALL FLOW DETECTORS/SWITCHES, COORDINATE REQUIREMENTS, QUANTITIES, AND LOCATIONS WITH THE SPRINKLER CONTRACTOR
DH	MAGNETIC DOOR HOLDER - CONTRACTOR TO CONNECT TO 120V CIRCUIT. DOOR HOLDERS SHALL RELEASE UPON ACTIVATION OF THE FIRE ALARM SYSTEM
FACP	FIRE ALARM CONTROL PANEL
FAAP	FIRE ALARM ANNUNCIATOR PANEL - BACK BOX WITH 1" CONDUIT MINIMUM TO ACCESSIBLE CEILING
S	SMOKE DETECTOR - DEEP 4" SQUARE BOX WITH SINGLE GANG PLASTER RING WITH CABLE IN 3/4" CONDUIT TO ACCESSIBLE CEILING.
SS	SINGLE STATION SMOKE DETECTOR 120 VOLT WITH BATTERY BACKUP AND INTERCONNECTED TO ALL SMOKE DETECTORS IN UNIT.
HD	FIRE ALARM DUCT DETECTOR
H	HEAT DETECTOR - DEEP 4" SQUARE BOX WITH SINGLE GANG PLASTER RING WITH CABLE IN 3/4" CONDUIT TO ACCESSIBLE CEILING.
AM	ADDRESSABLE INPUT/OUTPUT MODULE
XX	FIRE ALARM WALL MOUNTED STROBE UNIT - DEEP 4" SQUARE BOX WITH SINGLE GANG PLASTER RING WITH CABLE IN 3/4" CONDUIT TO ACCESSIBLE CEILING (MOUNTING HEIGHT AS PER NFPA 72, ALL DEVICES SHALL BE AT SAME HEIGHT) XX DENOTES CANDELA RATING
XX	FIRE ALARM CEILING MOUNTED STROBE - XX DENOTES CANDELA RATING
XX	FIRE ALARM WALL MOUNTED HORN/STROBE UNIT - DEEP 4" SQUARE BOX WITH SINGLE GANG PLASTER RING WITH CABLE IN 3/4" CONDUIT TO ACCESSIBLE CEILING (MOUNTING HEIGHT AS PER NFPA) XX DENOTES CANDELA RATING
C XX	FIRE ALARM CEILING MOUNTED HORN/STROBE - XX DENOTES CANDELA RATING
	FIRE ALARM WALL MOUNTED SPEAKER - DEEP 4" SQUARE BOX WITH SINGLE GANG PLASTER RING WITH CABLE IN 3/4" CONDUIT TO ACCESSIBLE CEILING (MOUNTING HEIGHT AS PER NFPA 72, ALL DEVICES SHALL BE AT THE SAME HEIGHT)
C	FIRE ALARM CEILING MOUNTED SPEAKER
XX	FIRE ALARM WALL MOUNTED SPEAKER/STROBE UNIT - DEEP 4" SQUARE BOX WITH SINGLE GANG PLASTER RING WITH CABLE IN 3/4" CONDUIT TO ACCESSIBLE CEILING (MOUNTING HEIGHT AS PER NFPA 72, ALL DEVICES SHALL BE AT THE SAME HEIGHT) XX DENOTES CANDELA RATING
C XX	FIRE ALARM CEILING MOUNTED SPEAKER STROBE - XX DENOTES CANDELA RATING
	SPRINKLER ALARM BELL (BY OTHERS) - PROVIDE DEDICATED LOW VOLTAGE FIRE ALARM CIRCUIT FROM THE FIRE ALARM CONTROL PANEL. COORDINATE WITH SPRINKLER CONTRACTOR.

NOTES:
1. ITEMS ON THIS SCHEDULE ARE NOT NECESSARILY SHOWN ON PLANS.

DELIVER

ELECTRICAL GENERAL NOTES

1. ELECTRICAL INSTALLATION SHALL BE IN ACCORDANCE WITH THE CURRENT EDITION OF THE NATIONAL ELECTRICAL CODE (NEC) AS WELL AS ANY LOCAL CODES AND ORDINANCES.
2. MAINTAIN PROPER WORKING SPACE CLEARANCES ABOUT ELECTRICAL EQUIPMENT PER NEC ARTICLE 110.26.
3. FULLY COORDINATE ALL ELECTRICAL REQUIREMENTS OF THIS CONSTRUCTION CONTRACT. EACH SYSTEM SHALL BE COMPLETE AND FULLY FUNCTIONAL. THIS INCLUDES MECHCANICAL, PLUMBING, OWNER PROVIDED AND CONTRACTOR PROVIDED EQUIPMENT. CONTRACTOR TO REFER TO EQUIPMENT INSTALLATION DOCUMENTS AND SHOP DRAWINGS PRIOR TO ANY ROUGH-IN.
4. CONTRACTOR SHALL COORDINATE CIRCUIT BREAKER AND FUSE SIZES FOR MECHANICAL EQUIPMENT PER SUBMITTED EQUIPMENT MANUFACTURER'S RECOMMENDED NAMEPLATE RATINGS PRIOR TO SHOP DRAWING PHASE OF PROJECT.
5. INTERRUPTION OF SERVICE: BEFORE ANY EQUIPMENT IS SHUT DOWN FOR DISCONNECTING OR TIE-INS, ARRANGEMENTS SHALL BE MADE WITH THE ARCHITECT AND THIS WORK SHALL BE DONE AT THE TIME BEST SUITED TO THE OWNER. OUTAGES MUST BE SCHEDULED THROUGH THE ARCHITECT. THE ARCHITECT SHALL REVIEW EXTENT, LENGTH, AND TIMING OF OUTAGES. SERVICES SHALL BE RESTORED THE SAME DAY. PROVIDE TEMPORARY POWER OR OTHER SERVICES AS REQUIRED DURING OUTAGES. ALL OVERTIME OR PREMIUM COSTS ASSOCIATED WITH THIS WORK SHALL BE INCLUDED IN THE BASE BID.
6. COORDINATE LOCATION OF ELECTRICAL EQUIPMENT WITH PIPES AND DUCT WORK BEING SUPPLIED BY OTHER DIVISIONS. THE EQUIPMENT SPACE INCLUDING ALL REFERENCED NEC CLEARANCES SHALL BE MAINTAINED. IF ANY PIPES OR DUCT WORK VIOLATE ANY ELECTRICAL CLEARANCE REQUIREMENTS, IT SHALL BE REMOVED AND RELOCATED AT TEH CONTRACTOR'S EXPENSE. DRIP PANS ARE NOT PERMITTED UNLESS SPEVIFICALLY CALLED FOR IN THE CONSTRUCTION DOCUMENTS
7. IT SHALL BE THE CONTRACTOR'S RESPONSIBILITY TO SEE THAT ALL EQUIPMENT THAT MAY REQUIRE MAINTENCANCE AND OPERATION ARE READILY ACCESSIBLE, REGARDLESS OF THE DIAGRAMMATIC LOCATION SHOWN ON THE DRAWINGS. ALL CONNECTIONS TO FIXTURES AND EQUIPMENT SHOWN ON THE DRAWINGS SHALL BE CONSIDERED DIAGRAMMATIC UNLESS OTHERWISE INDICATED BY A SPECIFIC DETAIL ON THE DRAWINGS. THE ACTUAL CONNECTIONS SHALL BE MADE TO FULLY SUIT THE REQUIREMENTS OF EACH CASE AND ADEQUATELY PROVIDE FOR SERVICING.
8. CONTRACTOR SHALL TAMP AND BACKFILL ALL TRENCHES. TRENCHES SHALL BE LEVEL WITH FINISH GRADE.
9. CONTRACTOR SHALL VISIT THE SITE AND DETERMINE THE EXTENT OF DEMOLITION WORK AND NEW WORK NEEDED FOR THIS PROJECT.
10. CONTRACTOR SHALL BECOME FAMILIAR WITH THE PROJECT SCOPE, CONTRAINTS, UTILITY CONNECTIONS, AND BUILDIG SERVICES.
11. CONTRACTOR SHALL GIVE RIGHT TO REFUSAL OF SALVAGE TO THE OWNER. IF THE OWNER ELECTS TO NOT KEEP SALVAGE, CONTRACTOR SHALL REMOVE SALVAGE BY LAWFUL MEANS.
12. DRAWINGS ARE SCHEMATIC AND DIAGRAMMATIC IN NATURE. DRAWINGS SHALL NOT BE SCALED. COORDINATE ROUTING OF SERVICES WITH SITE CONDITIONS AND WITH WORK OF OTHER TRADES.
13. FIELD VERIFY DIMENSIONS PRIOR TO ORDERING, FABRICATING, AND ERECTION OF MATERIAL AND/OR EQUIPMENT. NOTIFY THE ENGINEER OF DISCREPANCIES IN A TIMELY MANNER.
14. SEAL PENETRATIONS THROUGH THE BUILDING ENVELOPE.
15. PENETRATIONS THROUGH RATED WALLS, FLOORS, PARTITIONS AND ASSEMBLIES SHALL BE INSTALLED AND FIRESAFED TO MEET UL. FIRE RESISTANCE LISTING AND NFPA REQUIREMENTS FOR THE PENETRATION.
16. COORDINATE DEVICES REQUIRING ACCESS PANELS WITH THE ARCHITECT AND OTHER TRADES.
17. DEVICE SYMBOLDS ALONG WITH DRAWINGS, DRAWING NOTES, AND SPECIFICATIONS ARE INTENDED TO PROVIDE A COMPLETE SYSTEM. CONTRACTOR TO COORDINATE WITH ALL TRADES TO PROVICE A COMPLETE SYSTEM.

YEAGER, WATSON & ASSOCIATES, LLC
ARCHITECTS
TELEPHONE (318) 202-5708
FACSIMILE (318) 202-5722
118 SOUTH TRENTON STREET
RUSTON, LOUISIANA 71270

IMPROVEMENTS TO
J.I. BARRON ELEMENTARY SCHOOL
PINEVILLE, LA
RPSB# 52-26-01
Owner : Rapides Parish School Board
Pineville, Louisiana

STATE OF LOUISIANA
DAVID CARROLL
REG. NO. 41691
REGISTERED
PROFESSIONAL ENGINEER
09/24/25
ELECTRICAL ENGINEERING

ELECTRICAL LEGEND

REVISIONS:

DATE: SEPTEMBER 2025

JOB NUMBER: 2025-02

E000 | X OF X

M&E CONSULTING
1304 Bertrand Dr. Suite F7, Lafayette, LA 70506
13201 Northwest Fwy. Ste 633, Houston, TX
(337)234-7474
Mechanical Gabrielle Wehner
Contact: gabrielle@meconsulting.com
Electrical Terry Kirsch
Contact: Terry@meconsulting.com
PROJECT No.: 25051.00